

**I**N 1981 a good-looking newcomer arrived on the microcomputer scene. Its impressive pedigree and range of connections aroused interest. Its performance caused a sensation.

That newcomer was the British Broadcasting Corporation Microcomputer, one of the great success stories of the computer industry. A key feature of the BBC's Computer Literacy Project, it was chosen for seven out of every ten micros bought for UK schools and five out of ten used for medical applications. In homes and factories, offices and laboratories, the BBC Micro's user friendliness and ability to solve problems has won it countless friends and admirers.

Now, the concepts that were the key to that success have been incorporated in a new range of advanced microcomputers – the BBC Master Series.

#### **The BBC Master 128**

The Master 128 is the foundation stone of the BBC Master Series.

For a start, it is a word processor. The Master 128's professional typewriter keyboard and powerful word-processing software enable you to prepare reports, essays and letters which are word perfect.

It is also a spreadsheet calculator. The popular and easy-to-learn spreadsheet program is ideally suited to applications involving budgeting, planning, estimating or any repetitive calculations.

#### **The Series**

The Master series provides all the features for which BBC Micros have become renowned. The ability to link many computers together in a network enabling



them to share data and resources, the highly regarded BBC BASIC programming language, and the flexibility that has led to BBC Micros being chosen for applications as diverse as electronic funds transfer and satellite communications.

The sophisticated graphics facilities of the Master Series are ideally suited to computer-aided drawing and design or for the computer generation of graphs, charts and diagrams.

If your interest is in creating your own programs, the Master Series provides you with the latest version of BBC BASIC, widely regarded as the best BASIC.

These proven capabilities are combined with the best of modern technological developments. By the addition of an easy-to-fit plug-in card the Master 128 can be upgraded at any time to the Master Turbo, Master 512 or the

Master Scientific.

The Master Scientific brings the power of 32-bit processing to a microcomputer. The Master 512 offers a 16-bit processor with 512 Kbyte of random access memory. And in the Turbo version, the Master Series achieves speeds of execution which are faster than virtually any other personal computer.

#### **Compatibility**

The Master Series represents a continuous evolutionary development of the BBC Micro; unlike some other computer families where each 'new generation' leaves you looking for the missing link.

The Master Series is generally upwardly compatible with previous BBC Micros. In other words, new features have been added without losing existing ones.

This means that an enormous range of add-ons and peripheral devices, plus a vast software library with many thousands of titles, are available for use with the Master Series – now.

The Master 512, through its DOS+ operating system, can be compatible with software written for MS-DOS, CP/M-86 or GEM, the most popular operating systems for the business environment.

#### **The Reliability of Experience**

The Master Series incorporates the experience gained by Acorn Computers on more than 700,000 microcomputers over five years of operation. Acorn's design skills and production expertise ensure that the Master Series maintains the BBC Micro's tradition of high engineering standards and its reputation for reliability. And if you want advice or assistance, it is readily available from an existing network of dealers throughout the UK.

#### **Mastering The Future**

Above all, the Master Series has inherited and developed the BBC Micro's unique ability to bridge the gaps between home and scientific use, between education, business and industry. No other micro has demonstrated this versatility in the past; no other micro looks like doing so in the future.

The Master Series brings together hardware and software excellence, professionalism and experience. It is a combination that will make the Master Series the yardstick by which all microcomputers are judged throughout the second half of the 1980s.



# THE MASTER SERIES



# THE MASTER SERIES SPECIFICATIONS



## THE MASTER 128

### CPU

65C12  
2 MHz clock frequency

### RAM

64 Kbytes main  
64 Kbytes sideways, four 16 Kbyte pages  
50 bytes CMOS battery backed  
20 bytes used by fired firmware  
10 bytes reserved for future Acorn use  
10 bytes reserved for 3rd party applications  
10 bytes available to user applications

User RAM is not affected by filing system workspace  
Character set (ASCII 32-255) can be redefined with no loss of user RAM

### ROM

128 Kbytes  
CONTENTS:  
35 Kbytes Operating System with extended graphics and Terminal software  
16 Kbytes BBC BASIC v 4.0  
16 Kbytes EDIT, program and text Editor  
13 Kbytes VIEW v 3.0, wordprocessor  
16 Kbytes VIEW/SHEET, spreadsheet  
16 Kbytes ADFS, Advanced disc filing system  
16 Kbytes 1770 DFS, BBC model B+ compatible

### Internal ROM sockets

2x128 or 256 Kbit capability  
1x128 Kbit capability  
Total sideways memory usable at any time (ROM or RAM) 256 Kbytes inc 96 Kbyte fitted firmware

### Cartridge Sockets

2 Enhanced Acorn cartridge sockets  
Internal '1 MHz bus' updated to 2 MHz bus speed  
256 Kbyte ROM capacity, per socket  
Sound input and output

### Disc Interface

Shugart standard  
SUPPORTS:  
MFM, double data density  
FM, single data density  
40 or 80 track drives with a 6mS step rate or better

Formatted capacity, 320 Kbytes - MFM, 80 track, per surface - total 1.28 Mbyte on twin 80 track double-sided drives 34 way IDC connector

### Optional Network Interface

Acorn ECONET  
16 Kbytes ANFS ROM  
5 pin DIN socket

### Parallel Printer Interface

8 bit Centronics compatible  
26 way IDC connector

### Serial Interface

RS423 75-9600 baud software selectable  
Independent Rx/Tx baud rate selection  
5 pin DIN socket

### Display

MODES:  
8 standard modes + 8 'Shadow' modes  
Mode 0 2 colour  
80x32 text 640x256 graphics  
Mode 1 4 colour  
40x32 text 320x256 graphics  
Mode 2 8 colour + 8 flash options  
20x32 text 160x256 graphics

Mode 3 2 colour  
80x25 text only  
Mode 4 2 colour  
40x32 text 320x256 graphics  
Mode 5 4 colour  
20x32 text 160x256 graphics

Mode 6 2 colour  
40x25 text only  
Mode 7 8 colour  
40x24 'Teletext' text and graphics  
8 Shadow modes provide the same displays without affecting user memory

Graphics commands extend colour range by colour mixing

### OUTPUTS:

Phono socket  
UHF channel 36, full colour  
BNC connector  
Composite Video 1V peak to peak, monochrome  
6 pin DIN socket  
RGB TTL level/+5 V/+ve or -ve sync

### Sound

4 channels full software control  
Internal speaker 5.0cm  
Phono socket output for 16 Ohm speaker or pre-amp

### User Port

10 bit memory mapped bi-directional TTL compatible  
+5 volts available  
20 way IDC connector

### 1 MHz Bus

General purpose Bus extender  
Audio output and input  
Internal or external, software selectable  
34 way IDC connector (external)

### External TUBE

Custom interface for the connection of second processors  
40 way IDC connector (external)

### Internal TUBE

Custom interface for the connection of co-processors  
2x12 way connectors  
Internal or External TUBE selectable by software

### Analogue Input

4 channel Analogue to Digital conversion  
8 bit accuracy  
1.8 volt reference voltage  
Light pen strobe connection to CRT  
15 way D-type connector  
Accepts external reference voltage for higher precision

### Cassette Interface

300 - 1200 CUTS standard, speed is software selectable  
Output 200 mV peak to peak  
Input 50 mV to 5 V  
Motor control relay, 1 Amp at 24 Volts DC  
7 pin DIN connector

### Real Time Clock

Battery back-up, Lithium cell, minimum 1 year life  
Information can be called from MOS, BASIC and other languages  
Time/Day/Date/Year

### Keyboard

64 key QWERTY keyboard with 2 key rollover and auto repeat (rate and delay selectable by software)  
10 function keys  
19 key numeric pad  
Screwdriver-operated BREAK key lock

### Auxiliary power socket

+ 12 Volts  
+ 5 Volts  
- 5 Volts  
Power available is dependent on internal options

### Power Input (UK)

216 to 264 V.AC (50 Hz) Rating 100 Watts  
0.5 Amps

### Dimensions

Width: 476 mm  
Depth: 346 mm  
Height: 79 mm

### Software

1 tape + 1 disc (40/80 format)  
Welcome suite  
Welcome utilities  
ADFS utilities  
BAS 128 - BBC BASIC for sideways RAM use, 64 K free RAM

### Documentation

Welcome Guide, this provides an introduction to the Master 128's hardware and firmware  
VIEW and ViewSheet reference cards  
FUNCTION KEY STRIPS  
VIEW/ViewSheet/EDIT/Terminal  
OPTIONAL REFERENCE GUIDES:  
Reference Guides 1 and 2  
VIEW and ViewSheet Guides  
Advanced Reference Guide

## THE MASTER TURBO

I/O processor - uses the Master Series 128 CPU  
All features of the Master 128 are provided as described above with the following additional features:

### Language processor

65C102 8 bit CMOS  
Clock frequency 4 MHz  
MEMORY:  
RAM 64 Kbytes  
ROM 4 Kbytes - TUBE communications code  
VIEW automatically relocated on transfer from I/O processor memory  
Typical speed increase, 50% (HI-BASIC vs BASIC v4, PCW benchmarks)  
Operating system support for parallel processing (eg 'GOIO')  
HI-BASIC, HI-EDIT and Printer-Buffer extender supplied on disc

## THE MASTER 512

I/O processor - uses the Master Series 128 CPU  
All features of the Master 128 are available as described above with the following additional features:

### Language processor

80186 16 bit  
Clock frequency 10 MHz

MEMORY:  
RAM 512 Kbytes  
ROM up to 256 Kbytes  
A Mouse

### Software:

on disc  
Digital Research DOS+  
DOS+ provides compatibility with MSDOS version 2 and CPM 86  
The GEM Collection from Digital Research:  
GEM Desk Top  
GEM Paint  
GEM Write

### Documentation:

1 manual

## THE MASTER SCIENTIFIC

I/O processor - uses the Master Series 128 CPU

All features of the Master 128 are provided as described above with the following additional features:

### Language processor:

National Semiconductor 32016 32 bit  
Clock frequency 8 MHz  
Floating point processor NS 32081  
MEMORY:  
RAM 512 Kbytes  
ROM 16 Kbytes  
PANDORA operating system core  
TUBE communications code  
BBC BASIC equivalent to v 4.0

### Optional software:

on disc  
PANOS operating system including: Editor, Linker and Utilities  
FORTRAN 77 -  
Conforms to ANSI X3.9-1978 and ISO 1539-1980  
ISO PASCAL -  
Conforms to BS 6192-1982  
C - Conforms closely to the description in the book 'The C Programming Language' by Kernighan & Ritchie  
32000 series macro assembler  
Library support, as appropriate, for FORTRAN, PASCAL and C

### Documentation:

Master Scientific User Guide  
PANOS Guide to Operations\*  
PANOS Programmer's Reference Manual\*  
BBC BASIC Reference Manual  
FORTRAN 77 Reference Manual\*  
ISO PASCAL Reference Manual\*  
C Reference Manual\*  
Acorn 32000 ASSEMBLER Reference Manual\*

Function key card booklet\*

\* available separately

## THE MASTER ECONET TERMINAL

Processor and RAM as Master Series 128

### ROM

64 Kbytes  
CONTENTS:  
32 Kbytes Operating system  
16 Kbytes BBC BASIC  
16 Kbytes Advanced Network Filing System

### Display

Composite video as Master 128  
RGB as Master 128

### Network Interface Card

Fitted standard

### Cartridge sockets

as Master 128

### Internal Tube connector

as Master 128

NB 6522 User VIA chip is not fitted but is available as an option.

In this brochure the initials BBC refer to the British Broadcasting Corporation.

The following are trademarks of Acorn Computers Limited: Econet, Tube, View, Viewsheet, Music 500, PANOS and ET. CPM-86, DOS+, DOS 4.1, GEM, GEM COLLECTION, GEM PAINT, GEM WRITE and GEM DESK TOP are trademarks of Digital Research Inc. Prestel is a trademark of British Telecommunications PLC. The products described in this brochure are subject to improvement and change. © 1986 Acorn Computers Limited Design and art direction: Carrods Graphic Design, Cambridge

THE MASTER SERIES



HEAD OFFICE:  
Acorn Computers Limited  
Fulbourn Road  
Cherry Hinton  
Cambridge CB1 4JN  
England

Telephone (0223) 245200  
Telex 81 7875 Acorn G  
Fax (0223) 210685

ALL ENQUIRIES TO:  
Acorn Computers Limited  
Cambridge Technopark  
645 Newmarket Road  
Cambridge CB5 8PD  
England

Telephone (0223) 214411  
Telex 81 152 Acnmmr G  
Fax (0223) 214382  
Viewdata (0223) 243642



Acorn APP83  
The choice of experience.